

# ACR1252U NFC Forum Certified Reader



**Technical Specifications V1.03** 



# **Table of Contents**

1.0.	Introduction	3
2.0.	Features	4
3.0.	Typical Applications	5
4.0.	Technical Specifications	6



### 1.0. Introduction



The ACR1252U is a PC-linked NFC Reader that is NFC Forum-certified.

The ACR1252U runs on the 13.56 MHz contactless technology and supports ISO 14443 Type A and B cards, MIFARE®, FeliCa, ISO 18092—compliant NFC tags, and other NFC devices. It has an ISO 7816—compliant Class A SAM (Secure Access Module) slot which can be used together with a SAM card for key diversification and mutual authentication, providing high level of security in contactless transactions. Post-deployment firmware upgrade is also supported, eliminating the need for additional hardware modification.

ACR1252U is capable of the three modes of NFC, namely, Card Reader/Writer, Card Emulation and Peer-to-Peer Communication. These NFC features make the ACR1252U ideal for NFC applications like Smart Posters for advertising and marketing purposes with most NFC-enabled mobile phones and SIM cards in the market.



### 2.0. Features

- USB Full Speed Interface
- CCID-compliant
- Smart Card Reader:
  - Contactless Interface:
    - Read/Write speed of up to 424 Kbps
    - Built-in antenna for contactless tag access, with card reading distance of up to 50 mm (depending on tag type)
    - Supports ISO 14443 Part 4 Type A and B cards, MIFARE Classic®, FeliCa, and all four types of NFC (ISO/IEC 18092 tags)
    - Built-in anti-collision feature (only one tag is accessed at any time)
    - NFC Support:
      - Card reader/writer mode
      - Peer-to-Peer mode
      - Card Emulation mode
  - o SAM Interface:
    - One SAM Slot
    - Supports ISO 7816-compliant Class A SAM cards
- Built-in Peripherals:
  - User-controllable bi-color LED
  - User-controllable buzzer
- Application Programming Interface:
  - Supports PC/SC
  - Supports CT-API (through wrapper on top of PC/SC)
- USB Firmware Upgradeability
- Supports Android<sup>™</sup> 3.1 and later<sup>1</sup>
- Compliant with the following standards:
  - EN 60950/IEC 60950
  - o ISO 18092
  - o ISO 14443
  - o ISO 7816 Class A (SAM Slot)
  - NFC Forum Certification Mark
  - Felica Performance Certification
  - o PC/SC
  - CCID
  - o CE
  - o FCC
  - o RoHS 2
  - o REACH
  - o J-LIS (Japan)
  - VCCI (Japan)
  - o MIC (Japan)
  - KC (Korea)
  - Microsoft® WHQL

<sup>&</sup>lt;sup>1</sup> Uses an ACS-defined Android Library




# 3.0. Typical Applications

- e-Government
- e-Banking and e-Payment
- e-Healthcare
- Transportation
- Network Security
- Access Control
- Loyalty Program
- Smart Poster/URL Marketing
- P2P Communication



## 4.0. Technical Specifications



<b>B</b> 1								٠.	
Phys	ıcaı	CI	าล	ra	CI	:er	'IS	П	CS

### USB Host Interface

Protocol USB CCID
Connector Type Standard Type A
Power Source From USB port

Speed......USB Full Speed (12 Mbps)

Supply Voltage...... 5 V

### **Contactless Smart Card Interface**

Standard ...... ISO/IEC 18092 NFC, ISO 14443 Type A & B, MIFARE, FeliCa

Protocol ...... ISO 14443 T=CL for ISO 14443-4–compliant cards

......T=CL Emulation for MIFARE Classic, ISO 18092, FeliCa and NFC tags

Operating Frequency ...... 13.56 MHz

Operating Distance ...... Up to 50 mm (depending on tag type)

Smart Card Read/Write Speed...... 106 Kbps, 212 Kbps, 424 Kbps

Antenna Size...... 50 mm × 40 mm

### SAM Card Interface

Number of Slot ...... 1 Standard SIM-sized Card Slot

Standard ...... ISO 7816, Class A (5 V)

Protocol.....T=0;T=1

Smart Card Read/Write Speed...... 9.6 Kbps – 215 Kbps Card Connector Type...... SAM Slot 0: Contact

### Built-in Peripherals

LED ...... 1 bi-color: Red and Green

Buzzer......Monotone

### Other Feature

Firmware Upgrade ...... Supported

### **Application Programming Interface**

PC-linked mode......PC/SC

### Operating Conditions

Temperature ...... 0  $^{\circ}$ C – 50  $^{\circ}$ C

Humidity ...... Max. 90% (non-condensing)

MTBF ...... 500,000 hrs



### **Certifications/Compliance**

EN 60950/IEC 60950, ISO 18092, ISO 14443, ISO 7816 (SAM Slot), USB Full Speed, NFC Forum Certification, Felica Performance Certification, PC/SC, CCID, CE, FCC, RoHS 2, REACH J-LIS (Japan), VCCI (Japan), MIC (Japan), KC (Korea), Microsoft® WHQL

### **Device Driver Operating System Support**

Windows® CE 5.0, Windows® CE 6.0, Windows® Embedded Compact 7, Windows® XP, Windows Vista®, Windows® 7, Windows® 8, Windows® 8.1, Windows® 10

Windows® Server 2003, Windows® Server 2003 R2, Windows® Server 2008, Windows® Server 2008 R2, Windows® Server 2012, Windows® Server 2012 R2, Windows® 2016

Linux®, Mac OS®, Solaris, Android™ 3.1 and later





































Android is a trademark of Google Inc. Linux® is the registered trademark of Linus Torvalds in the U.S. and other countries. Mac OS is a trademark of Apple Inc., registered in the U.S. and other countries. Microsoft, Windows and Windows Vista are registered trademarks of Microsoft Corporation in the United States and/or other countries.

MIFARE and MIFARE Classic are registered trademarks of NXP B.V. and are used under license. The Certification Mark is a trademark or registered trademark of NFC Forum, Inc. in the United States and in other countries.